

## N-Channel Enhancement Mode Power MOSFET

### Description


The PE6986E uses advanced trench technology to provide excellent  $R_{DS(ON)}$ , low gate charge and operation with gate voltages as low as 2.5V. This device is suitable for use as a load switch or in PWM applications. It is ESD protected.

### General Features


- $V_{DS} = 20V, I_D = 6.5A$
- $R_{DS(ON)} < 15m\Omega @ V_{GS}=4.5V$
- $R_{DS(ON)} < 16m\Omega @ V_{GS}=3.8V$
- $R_{DS(ON)} < 20m\Omega @ V_{GS}=2.5V$
- ESD Rating: 2000V HBM
- High power and current handling capability
- Lead free product is acquired
- Surface mount package

### Application

- PWM application
- Load switch



Schematic diagram



Marking and pin Assignment



SOT23-6 top view

### Absolute Maximum Ratings ( $T_A=25^\circ C$ unless otherwise noted)

Parameter	Symbol	Limit	Unit
Drain-Source Voltage	$V_{DS}$	20	V
Gate-Source Voltage	$V_{GS}$	$\pm 10$	V
Drain Current-Continuous	$I_D$	6.5	A
Drain Current-Pulsed <sup>(Note 1)</sup>	$I_{DM}$	30	A
Maximum Power Dissipation	$P_D$	1.5	W
Operating Junction and Storage Temperature Range	$T_J, T_{STG}$	-55 To 150	$^\circ C$

### Thermal Characteristic

Thermal Resistance, Junction-to-Ambient <sup>(Note 2)</sup>	$R_{\theta JA}$	83.3	$^\circ C/W$
---	-----------------	------	--------------

### Electrical Characteristics ( $T_A=25^\circ C$ unless otherwise noted)


Parameter	Symbol	Condition	Min	Typ	Max	Unit
<b>Off Characteristics</b>						
Drain-Source Breakdown Voltage	$BV_{DSS}$	$V_{GS}=0V, I_D=250\mu A$	20	-	-	V
Zero Gate Voltage Drain Current	$I_{DSS}$	$V_{DS}=16V, V_{GS}=0V$	-	-	1	$\mu A$

Parameter	Symbol	Condition	Min	Typ	Max	Unit
Gate-Body Leakage Current	$I_{GSS}$	$V_{GS}=\pm 8V, V_{DS}=0V$	-	-	$\pm 10$	$\mu A$
<b>On Characteristics</b> <sup>(Note 3)</sup>						
Gate Threshold Voltage	$V_{GS(th)}$	$V_{DS}=V_{GS}, I_D=250\mu A$	0.45	0.75	1.0	V
Drain-Source On-State Resistance	$R_{DS(ON)}$	$V_{GS}=4.5V, I_D=6.5A$	12	13	15	$m\Omega$
		$V_{GS}=3.8V, I_D=6.0A$	12.5	13.5	16	$m\Omega$
		$V_{GS}=2.5V, I_D=5.5A$	15.5	17	20	$m\Omega$
Forward Transconductance	$g_{FS}$	$V_{DS}=5V, I_D=6A$	-	20	-	S
<b>Dynamic Characteristics</b> <sup>(Note 4)</sup>						
Input Capacitance	$C_{iss}$	$V_{DS}=10V, V_{GS}=0V, F=1.0MHz$	-	750	-	PF
Output Capacitance	$C_{oss}$		-	110	-	PF
Reverse Transfer Capacitance	$C_{rss}$		-	80	-	PF
<b>Switching Characteristics</b> <sup>(Note 4)</sup>						
Turn-on Delay Time	$t_{d(on)}$	$V_{DS}=16V, R_L=1.5\Omega$ $V_{GS}=4.5V, R_{GEN}=3\Omega$ $I_{DS}=3A$	-	15		nS
Turn-on Rise Time	$t_r$		-	10		nS
Turn-Off Delay Time	$t_{d(off)}$		-	20		nS
Turn-Off Fall Time	$t_f$		-	30		nS
Total Gate Charge	$Q_g$	$V_{DS}=16V, I_{DS}=3A,$ $V_{GS}=4.5V$ $I_{DS}=3A$	-	12		nC
Gate-Source Charge	$Q_{gs}$		-	4	-	nC
Gate-Drain Charge	$Q_{gd}$		-	3	-	nC
<b>Drain-Source Diode Characteristics</b>						
Diode Forward Voltage <sup>(Note 3)</sup>	$V_{SD}$	$V_{GS}=0V, I_{DS}=1A$	0.4	-	1.0	V
Diode Forward Current <sup>(Note 2)</sup>	$I_s$		-	-	6	A


**Notes:**

1. Repetitive Rating: Pulse width limited by maximum junction temperature.
2. Surface Mounted on FR4 Board,  $t \leq 10$  sec.
3. Pulse Test: Pulse Width  $\leq 300\mu s$ , Duty Cycle  $\leq 2\%$ .
4. Guaranteed by design, not subject to production


### Typical Electrical and Thermal Characteristics




**Figure 1:Switching Test Circuit**




**Figure 2:Switching Waveforms**




**Figure 3 Power Dissipation**









**Figure 4 Safe Operation Area**




**Figure 5 Output Characteristics**



**Figure 6 Drain-Source On-Resistance**





**Figure 13 Normalized Maximum Transient Thermal Impedance**

**SOT23-6 PACKAGE INFORMATION**